

Continuing Education Bulletin: Firmware upgrade for the TLS-450 and TLS-450PLUS

This Continuing Education Bulletin provides additional information to Veeder-Root service network and technicians on how to perform a firmware upgrade on the TLS-450 and TLS-450PLUS.

Continuing Education Bulletin: CEB_2015_08B

TLS-450:

To verify if the console has a Firmware upgrade available on a TLS-450:

1. Select Diagnostics 
2. Select Module 
3. Select Firmware Upgrade Tab 
4. Compare Current Firmware to Available Firmware

Device Directory		Device Assignments		Comm	Firmware Upgrade
Address	Module Type	Serial Number	Current Firmware Revision	Available Firmware Revision	
<input type="checkbox"/> B1.S1	USM - 16	0013130688	001-C	001-C	
<input type="checkbox"/> B1.S2	IOM - 14	0013130665	001-B	001-C	


5. If the Available firmware has a higher number or letter than continue to Perform a Firmware Upgrade.

To Perform a Firmware Upgrade on a TLS-450

1. Select Diagnostics 
2. Select Module 
3. Select Firmware Upgrade Tab 
4. Select the box to the left of the board you want to upgrade.

<input type="checkbox"/> B1.S1	USM - 16	0013130688	001-C	001-C
<input checked="" type="checkbox"/> B1.S2	IOM - 14	0013130665	001-B	001-C

5. Click on Install on the right side of the console 
6. Acknowledge the confirm download



- The screen will automatically refresh once the firmware upgrade has been completed.

Address	Module Type	Serial Number	Current Firmware Revision	Available Firmware Revision
<input type="checkbox"/> B1.S1	USM - 16	0013130688	001-C	001-C
<input type="checkbox"/> B1.S2	IOM - 14	0013130665	001-C	001-C

TLS-450PLUS:

To verify if the console has a Firmware upgrade available on a TLS-450PLUS:

- Select Menu 
- Go to Diagnostics 
- Select Module 
- Select Firmware Upgrade 

Address	Module Type	Serial Number	Current Firmware Revision	Available Firmware Revision
<input type="checkbox"/> B1.S1	INPUT/OUTPUT MODULE - 14	0011370222	001-B	001-C
B1.S2	UNIVERSAL SENS MODULE - 16	0011370223	001-C	001-C
<input type="checkbox"/> B1.S3	UNIVERSAL SENS MODULE - 16	0011370115	001-B	001-C

- Compare Current Firmware to Available Firmware
- If the Available firmware has a higher number or letter than continue to Perform a Firmware Upgrade.

To Perform a Firmware Upgrade on a TLS-450PLUS:

- Select Menu 

2. Select Diagnostics



3. Select Module



4. Select Firmware Upgrade



5. Select the box to the left of the board you want to upgrade.

Diagnostics > Module > Firmware Upgrade Print (0)			
Address	Module Type	Serial Number	Current Firmware Revision
<input checked="" type="checkbox"/> B1.S1	INPUT/OUTPUT MODULE - 14	0011370222	001-B

6. Click on Actions on the right side of the screen



Actions

7. Select Install



This button will be greyed out if an upgrade is not available.

8. Acknowledge the confirm download



9. The screen will automatically refresh once the firmware upgrade has been completed.

Diagnostics > Module > Firmware Upgrade Print (0)			
Address	Module Type	Serial Number	Current Firmware Revision
B1.S1	INPUT/OUTPUT MODULE - 14	0011370222	001-C